

XONE 42





The Xone:42 is a new, compact 4 -channel DJ mixer with USB audio interface, designed for DJ's of all abilities and experience from top pro DJ's to bedroom enthusiasts who want a compact quality mixer with pro features.

Integral to the mixer's design is a new feature - the 'X-FX' control - allowing signal to be sent to external FX, and returned to be combined with the now legendary Xone VCF filter system.

There's even a USB port which allows easy connection to a computer and integration of digital media, which can be used to play back music files from a laptop and to record mixes, or used with software as a digital DJ effects unit.

The Xone:42 is so neat and packed with useful features that it'll find a home in any bar, club or even your bedroom!



XONE:42	Desk mount	Rack ears(1)	Rack ears (2)	Packed
mm(") Width	305 (12)	355 (14)	483 (19)	490 (19.5)
mm(") Height	84 (3.3)	84 (3.3)	84 (3.3)	205 (8.1)
mm(") Depth	358 (14)	358 (14)	358 (14)	450 (17.7)
kg(lb) Weight	5 kg (11)			7 (15.4)

FEATURE LIST

4 dual stereo channels

Channels 1 & 4 have phono (RCA RIAA turntable) inputs or TRS jack line, while channels 2 and 3 are line/line

3 band EQ

All channels have +6dB to total kill EQ

X-FX send to external FX

Allows signal to be sent to external FX, and returned to be combined with VCF controls

VCF filter

Stereo filter with independent in/out, resonance & frequency controls

VCA Crossfader

with curve control from sharp attack for scratching to smooth attack for house style

USB 1.1 port

One stereo up to PC and one stereo back

Microphone input

On XLR, with 2-band EQ and level control

2 headphone outputs

1/4" and 3.5mm

Power supply

High performance internal switch-mode psu

Rack ears

Optional rack ears available

